

An Electron-Nucleon Double Spin Solid-State Quantum Computer

Gui Lu Long^{1,2,3,4}, Ying Jun Ma^{1,2}, and Hao-Ming Chen¹

¹Department of Physics, Tsinghua University, Beijing 100084, China

²Key Laboratory For Quantum Information and Measurements, Beijing 100084, China

³Center for Atomic and Molecular Nanosciences, Tsinghua University, Beijing 100084, China

⁴Institute of Theoretical Physics, Chinese Academy of Sciences, Beijing 100080, China

(February 1, 2008)

An electron-nucleon double spin(ENDOS) solid-state quantum computer scheme is proposed. In this scheme, the qubits are the nuclear spins of phosphorus ion implanted on the (111) surface of ²⁸Si substrate. An ¹³C atom on a scanning tunnelling probe tip is used both to complete single qubit and two-qubit control-not operation, and single qubit measurement. The scheme does not require interactions between qubits, and can accomplish two qubits without the use of SWAP gate. This scheme is scalable, and can be implemented with present-day or near-future technologies.

03.67.Lx, 07.79.Cz, 33.40.+f

Quantum computer(QC) is a worldwide scientific pursuit. To design a QC, one needs a two level quantum system to act as qubit and able perform single bit rotation, two qubit control-not operation and single qubit measurement. The system should also be robust against errors and decoherence. Many realization schemes have been put forward, for instance, liquid nuclear magnetic resonance [1,2], ion trap [3], cavity-QED [4], Josephson-junction qubit [5,6], quantum dot [7], nuclear spin qubit in solid state and liquid crystal [8], nuclear spin qubit in liquid crystal lattice [9], photon qubit [10], electron qubit [11], magnetic force scanning microscopy [12] are just a few names in this long list.

Nuclear spins are well isolated from environment, their coherence time is usually very long at low temperature [8]. Meanwhile, modern micro-fabrication technology is well developed, making solid state device a favorite choice. In Kane's proposal [8], these two advantages are combined. Logical operations are completed by using externally applied electric field and radio frequency pulses. One important feature of Kane's scheme is that it requires atomic size precision of the donor phosphorus ion, and delicate design of the spin measurement which is a feast for the present-day technology. Several alternative proposals have been put forward that do not need such high precision requirement, using scanning tunneling microscope(STM) or magnetic resonance force microscopy(MRFM) [12,13], nuclear spins at lattice structure [9,14]. Common in these schemes, are the use of gradient magnetic fields and the dipole-dipole interaction between neighboring qubits. In a gradient magnetic field, different qubits have different frequency so that it can be individually addressed. The (dipole-dipole) interaction between neighboring qubits is essential to construct the CNOT operation in these schemes. However, additional effort has to be made to cancel these dipole interaction and the next neighbor interaction when they are not used in the computation.

STM has been broadly used in various fields of research since its invention [14]. It can perform single atom engineering [15–19]. STM can manipulate a single atom or a molecule [15,20,21], and even doing so at room temperature. The spatial resolution of STM has reached the sub-Ångström range [22]. In particular, recent studies have demonstrated the possibility of detecting single spin state using the modulation effect of STM tunneling current [23–26]. This makes the STM a very good candidate for quantum computer design.

Here we propose an electron-nucleon double spin(ENDOS) solid state quantum computer that uses STM for single qubit addressing, operation, two-qubit operation and final state measurement. The ENDOS scheme is shown in Fig.1. Phosphorus ion arrays are deposited at the (111) surface of ²⁸Si substrate. Over the sample there is an STM tip which can move vertically and horizontally. The whole set-up is placed in an electron/nucleon magnetic resonance chamber where a strong static magnetic field B along z -axis is provided, and the radio frequency(r.f.) waves for electron/nucleon resonance manipulation is applied. The STM tip is made of carbon nano-tube with a ¹³C at the tip. This can be accomplished using present-day technology. Carbon nanotube can be conductive, it is very good for STM purpose. The donor ³¹P has nuclear spin $I = 1/2$, and it is used as **qubit**. The electrons of the phosphorus ions are weakly bound at low temperature, and they are used in manipulating the qubit. The distance of ³¹P ions in the substrate can be very large, say $a \geq 30nm$, since we do not require the interaction between neighboring qubits. This brings two benefits in quantum computation. First, there is not atomic-size precision requirement in fabrication. Second, ENDOS scheme is free from the trouble to decouple the dipole-dipole interaction between neighboring qubits when they are not in operation. Further the interaction of qubit between the next neighbor qubits cause considerable problems and this is also avoided in the ENDOS scheme.

The setup is placed at low temperature. In the presence of the magnetic field B , both nucleon and electron spin levels undergo Zeeman splitting. Because the gyromagnetic ratio of electron is negative, $g_e = -2$ for electron, spin down is its ground state. The ground state of phosphorus ion and ¹³C are spin up, because $g_n^p = 2.26$ and $g_n^c = 1.4048$ respectively. We label their ground states as $|0\rangle$. Before a quantum computation starts, one must first **initialize all**

the qubits into the ground state. This is done in two steps. First at a temperature of 1 K, all the electrons of the ^{31}P ions are in their ground state and half of the ^{31}P nuclear spins are in their ground state. Then we use the STM tip to measure the state of the ^{31}P nuclear spin, if it is in the excited state, a nuclear π pulse is applied to that qubit to flip its spin. In this way, the quantum computer can be initialized. Details will be given shortly for single qubit measurement.

Single qubit addressing is completed by moving the STM tip toward the qubit. The voltage of the STM tip changes the hyperfine interaction of the qubit, and hence the NMR frequency. When the STM tip is lifted up, the Hamiltonian of the nuclear spin-electron system of an ion can be written as [27]

$$H_{e-p} = g_e \mu_B B S_z - g_n^p \mu_n B I_z^p + h A_z S_z I_z^p. \quad (1)$$

where $h A_z$ is the hyperfine coupling energy between ^{31}P ion and the electron and its value can be measured by NMR experiment ($A_z = 120\text{MHz}$ was given in Ref. [28]), g_n^p is the Landé g -factor of ^{31}P ($g_n^p \simeq 2.26$) and $g_e = 2$, μ_B and μ_n are Bohr and nuclear magneton respectively. When we move the STM tip close to this ion, say at a distance of 10 Ångström, the tip-electron-ion system Hamiltonian becomes

$$\begin{aligned} H_{a-e-p} &= H'_{e-p} - g_n^a \mu_n B I_z^a + h A'_z S_z I_z^a \\ &= g_e \mu_B B S_z - g_n^p \mu_n B I_z^p + h A'_z S_z I_z^p - g_n^a \mu_n B I_z^a + h A'_z S_z I_z^a \end{aligned} \quad (2)$$

where I_z^a is the nuclear spin of the tip ^{13}C , its gyromagnetic ratio is $g_n^a \simeq 1.4048$. The $h A'_z$ is the hyperfine interaction between ^{31}P ion and the electron spin. A prime indicates that its value has been modified by the presence of the STM tip. $h A'$ is the hyperfine interaction between the electron and the ^{13}C ion where a prime also indicates a modification due to the presence of the phosphorus ion. Their exact values should be determined through experiment. The value of A' is of the order of a few GHz [12]. The value of A'_z is in the order of MHz. Without the STM tip modification, it was reported that $A_z = 120\text{MHz}$ [28].

To perform a **single qubit rotation**, we move the STP tip close to the qubit, say, 10 Ångströms. The ^{13}C nuclear spin and the electron spin are in ground state. The ^{31}P nuclear spin resonance frequency is now

$$\hbar \omega'_i = g_n^p \mu_n B - \hbar A'_z / 2, \quad (3)$$

which is different from that in the absence of the STM tip $\hbar \omega_i = g_n^i \mu_n B - \hbar A_z / 2$. Here the STM tip acts just like the A -gate in Kane's proposed quantum computer [8]. When a r.f. pulse with frequency at (3) is applied to the sample, the qubit under the STM tip is in resonance and undergo appropriate rotation just like in a NMR microscopy.

The biggest appeal of STM is the possibility of performing single qubit detection. **Single nuclear spin detection** can be done by the modulation of nuclear spin on the STM tunneling current. When the STM tip is close to a magnetic center, such as an electron spin, the STM tunneling current is modulated by the magnetic center's state. By analysing the spectrum of the tunneling current, one can determine the state of the qubit. The modulation effect of a localized electron spin to the tunneling current has already been observed in Si/Si₂ [26], Fe [23], and very recently in BDPA molecule [24]. Though there is no direct experiment of the single spin detection of ^{31}P , we believe that present technology is close to this purpose. As in Ref. [12], we assume that single qubit detection can be realized in this way. Here we assume the modulation of tunneling current is independent of the conducting electron spin polarization as suggested in Ref. [22], though spin-dependence mechanism is also suggested [30]. Nuclear spins can influence the electron through dipole interaction and thus causes a change in the modulation frequency. Both the STM ^{13}C nuclear spin and the phosphorus nuclear spin have modulation effects on the STM electron tunneling current. The electron tunneling current frequency is modulated by the ^{31}P nuclear spin and the ^{13}C nuclear spin in the following way:

$$f_{e,p=0} = g_e \mu_B B \mp \frac{1}{2} h A' + h A'_z / 2, \quad ^{31}\text{P} \text{ nuclear up} \quad (4)$$

$$f_{e,p=1} = g_e \mu_B B \mp \frac{1}{2} h A' - h A'_z / 2, \quad ^{31}\text{P} \text{ nuclear down}, \quad (5)$$

where the plus(minus) sign in front of $h A' / 2$ corresponds to ^{13}C in $|0\rangle$ state($|1\rangle$ state).

Two-qubit control-not operation construction is vital in a quantum computer scheme. Though there are many possible unitary operations in a quantum computation. It has been shown that all the unitary operations can be constructed by combining single qubit rotation and two-qubit CNOT operation. If these gates are constructed, then a quantum computer structure is constructed. We require the STM tip and all the electrons remain in ground states before and after the gate operation so that follow up gate operations using the same tip and electron condition. A CNOT gate is a conditional NOT gate. Suppose at the start, the control qubit state is $\alpha'|0\rangle_c + \beta'|1\rangle_c$ and the target qubit state is $\alpha|0\rangle_t + \beta|1\rangle_t$. A CNOT operation yields the following state: $\alpha'|0\rangle_c(\alpha|0\rangle_t + \beta|1\rangle_t) + \beta'|1\rangle_c(\alpha|1\rangle_t + \beta|0\rangle_t)$ where the subscripts c and t refer to control- and target- qubits respectively. We use ec and et subscripts to indicate the

state of the electrons of the control and target ions. Unlike in schemes that use neighboring dipole-dipole interaction where direct CNOT gate can only be constructed for neighbors, the control-qubit and the target-qubit in ENDOS scheme need not be neighbors. They can be any distance away. The CNOT gate implementation is implemented through 7 steps. The procedures involve first combined electron and nuclear resonant pulses to entangle the control qubit with its electron, then with the tip nuclear spin whose state is labeled by subscript a , and then with the target qubit electron, and then the target qubit. Then another combined sequence of pulses disentangle the electrons and the ^{13}C nuclear spin from the two qubits involved. As can be seen from equation (2), the nuclear spin resonance is only modulated by the electron spin state, whereas the electron resonance frequency is modulated by both the ^{13}C nuclear spin and the ^{31}P nuclear spin. The 7 steps for a CNOT gate operation are

1) Move the STM tip to the control qubit so that its resonance frequency is changed. Apply an electron π -pulse with frequency

$$f_{ec} = g_e \mu_e B + \frac{\hbar A'}{2} - \frac{\hbar A'_Z}{2}. \quad (6)$$

This pulse sequence changes the state of control-qubit electron if the control qubit is in state $|1\rangle$. The effect is

$$(\alpha'|0\rangle_c + \beta'|1\rangle_c)|0\rangle_{ec} \rightarrow (\alpha'|0\rangle_c|0\rangle_{ce} + \beta'|1\rangle_c|1\rangle_{ec}). \quad (7)$$

Thus it entangles the control qubit with its electron spin. This is already within the current technology. Entanglement of nuclear spin and electron spin at $T = 40\text{K}$ for radical CH has just been realized experimental by Mehring et al [29].

2) Apply a nuclear π -pulse with frequency

$$f_a = |g_n^a \mu_N B - \frac{\hbar A'}{2}|. \quad (8)$$

This frequency changes the state of STM tip ^{13}C nuclear spin on condition that the control electron is in state $|1\rangle$. After this pulse, the STM tip also joins the entanglement. The wave function goes through the following change

$$(\alpha'|0\rangle_c|0\rangle_{ce} + \beta'|1\rangle_c|1\rangle_{ec})|0\rangle_a \rightarrow \alpha'|0\rangle_c|0\rangle_{ce}|0\rangle_a + \beta'|1\rangle_c|1\rangle_{ec}|1\rangle_a. \quad (9)$$

3) Move the STM tip to the target ion and apply two electron π -pulses so that the electron spin of the target ion is flipped on condition that the STM tip is in state 1. Quantum mechanics ensures that even though the STM tip has been shifted elsewhere, the entanglement of the control qubit and its electron and the STM tip still holds. The two pulse frequencies are

$$f_{et1} = g_e \mu_B B + \frac{\hbar A'_Z}{2} + \frac{\hbar A'}{2}, f_{et0} = g_e \mu_B B - \frac{\hbar A'_Z}{2} + \frac{\hbar A'}{2} \quad (10)$$

respectively. They change the system into state

$$\alpha(\alpha'|0\rangle_t + \beta'|1\rangle_t)|0\rangle_{et}|0\rangle_c|0\rangle_{ec}|0\rangle_a + \beta(\alpha'|0\rangle_t + \beta'|1\rangle_t)|1\rangle_{et}|1\rangle_c|1\rangle_{ec}|1\rangle_a. \quad (11)$$

4) Apply a nuclear π -pulse on the target qubit with frequency

$$f_p = g_n^p \mu_N B - \frac{\hbar A'_Z}{2}. \quad (12)$$

This pulse change the system into state

$$\alpha(\alpha'|0\rangle_t + \beta'|1\rangle_t)|0\rangle_{et}|0\rangle_c|0\rangle_{ec}|0\rangle_a + \beta(\alpha'|1\rangle_t + \beta'|0\rangle_t)|1\rangle_{et}|1\rangle_c|1\rangle_{ec}|1\rangle_a. \quad (13)$$

Thus up to now, we have implemented the CNOT operation on the two qubits, but entangled with the two electrons and the STM tip. Next we disentangle the electrons and the STM tip from the control- and target- qubits.

5) Apply two electron π -pulses on the target ion electron with frequencies f_{et1} and f_{et0} respectively as given in Eqns. (10). These two electron pulses disentangle the target ion electron. The system state becomes

$$\alpha(\alpha'|0\rangle_t + \beta'|1\rangle_t)|0\rangle_{et}|0\rangle_c|0\rangle_{ec}|0\rangle_a + \beta(\alpha'|1\rangle_t + \beta'|0\rangle_t)|0\rangle_{et}|1\rangle_c|1\rangle_{ec}|1\rangle_a. \quad (14)$$

6) Move the STM tip back to the control qubit. Apply a nuclear π -pulse on the STM tip by using frequency f_a as given in (8). This disentangles the STM tip ^{13}C nuclear spin. The system state becomes

$$\alpha(\alpha'|0\rangle_t + \beta'|1\rangle_t)|0\rangle_{et}|0\rangle_c|0\rangle_{ec}|0\rangle_a + \beta(\alpha'|1\rangle_t + \beta'|0\rangle_t)|0\rangle_{et}|1\rangle_c|1\rangle_{ec}|0\rangle_a. \quad (15)$$

7) Apply an electron π pulse on the control ion electron by using frequency f_{ec} as given in (6). This disentangles the control ion electron. Then finally the state of the system is

$$\{\alpha(\alpha'|0\rangle_t + \beta'|1\rangle_t)|0\rangle_c + \beta(\alpha'|1\rangle_t + \beta'|0\rangle_t)|1\rangle_c\} |0\rangle_{et}|0\rangle_{ec}|0\rangle_a. \quad (16)$$

The speed of quantum computation in ENDOS depends on the duration of electron/nucleon pulse length and the time the STM tip takes to move from one position to another position. Typical nuclear pulse is of the order of micro-second and electron pulse is much shorter. The main factor is the STM tip speed. It is estimated that current commercial STM machine can make 8 scans per second on an area of $10\text{nm} \times 10\text{nm}$ with 258×258 points in each scan, which is equivalent to scan a point in $15\mu\text{s}$. Thus the estimated time for a CNOT gate is the order of $100\mu\text{s}$. If the decoherence time is 10 s, then it is sufficient to finish 10^5 gate operations. The speed can be accelerated if we make several STM tips working in parallel.

To summarize, an electron-nucleon double spin quantum computer scheme is proposed. Basic gate operations and measurement can be implemented by a STM tip with a ^{13}C . The scheme is within or close to the reach of present-day technology.

Helpful discussions with Prof. Kuzmany and Dr. Markus Arndt of University of Vienna, Dr Ille Gebeshuber of TU Vienna are gratefully acknowledged. We also thank Ms Li Xiao and Ms Fang Liu for help. This work is supported in part by China National Science Foundation, the National Fundamental Research Program, Contract No. 001CB309308 and the Hang-Tian Science foundation.

- [1] D. G. Cory, A. F. Fahmy, and T. F. Havel, *Proc. Natl. Acad. Sci. U.S.A.* **94**, 1634(1997).
- [2] N. Gershenfeld and I. Chuang, *Science* **275**, 350 (1997).
- [3] J. Cirac and p. Zoller, *Phys. Rev. Lett.* **75**, 4091 (1995); *Nature*, **404**, 579 (2000).
- [4] C. Monroe *et al.*, *Phys. Rev. Lett.* **75**, 4714 (1995).
- [5] Yu Makhlin, G. Schön, and A. Shnirman, *Rev. Mod. Phys.* **68**, 733 (1997).
- [6] J. E. Mooij, T. P. Orlando, L. Levitov, Lin Tian, Caspar H. van der Wal, Seth Lloyd, *Science*, **285**, 1036 (1999).
- [7] D. Loss and D.P. DiVincenzo, *Phys. Rev.* **A57**, 120 (1998).
- [8] B. E. Kane, *Nature* **393**, 133-136 (1998).
- [9] F. Yamaguchi and Y. Yamamoto, *Microelectron. Eng.* **47**, 273 (1999).
- [10] E. Knill, R. Laflamme, and G. J. Milburn, *Nature* **409** 46 (2001).
- [11] David P. DiVincenzo *Phys. Rev. A* **51**, 1015 (1995); W. Harneit, *Phys. Rev.* **A65**, 032322 (2002).
- [12] G. P. Berman, G. W. Brown, M. E. Hawley, and V. I. Tsifrinovich, *Phys. Rev. Lett.* **87**, 097902(2001); G. P. Berman, G. D. Doolen, P. C. Hammel, and V. I. Tsifrinovich, *Phys. Rev. Lett.* **86**, 2894 (2001).
- [13] G. P. Berman, G. D. Doolen, P. C. Hammel, V. I. Tsifrinovich, *Phys. Rev.* **B61**, 694 (2000).
- [14] G. Binnig, H. Rohrer, Ch. Gerber, and E. Weibel, *Appl. Phys. Lett.* **40**, 178 (1982); **49**, 57(1982).
- [15] D. M. Eigler and E. K. Schweizer, *Nature* **344**, 524 (1990); **352**, 600 (1991).
- [16] B. Neu, G. Meyer, and K. -H. Rieder, *Phys. Rev. Lett.* **79**, 697 (1997).
- [17] J. K. Gimzewski and C. Joachim, *Science* **283**, 1683 (1999).
- [18] G. Meyer, L. Bartels, S. Zöphel, E. Henze and K. -H. Rieder, *Phys. Rev. Lett.* **78**, 1512 (1997).
- [19] J. J. Schulz, R. Koch, and K. H. Rieder, *Phys. Rev. Lett.* **84**, 4597 (2000).
- [20] M. T. Cuberes, R. R. Schlittler, and J. K. Gimzewski, *Appl. Phys. Lett.* **69**, 3016 (1996).
- [21] T. W. Fishlock, A. Oral, R. G. Egdell and J. B. Pethica, *Nature* **404**, 743 (2000).
- [22] A. V. Balatsky and I. Martin, *quant-ph/0112407*.
- [23] Y. Manassen, I. Mukhopadhyay, and N. Ramesh Rao, *Phys. Rev.* **B61**, 16223 (2000).
- [24] C. Durkan and M. E. Welland, *Appl. Phys. Lett.* , **80**, 458 (2002).
- [25] X. de la Broïse, C. Delerue, M. Lannoo. B. Grandidier, and D. Sti'evenard, *Phys. Rev.* **B61**, 2138 (2000).
- [26] Y. Manassen, *J. Mag. Reson.* , **126**, 133 (1997).
- [27] C. P. Slichter, *Principles of Magnetic Resonance*, (Springer-Verlag, Berlin, (1990).
- [28] G. Feher, *Phys. Rev.*, **114**, 1219 (1959).
- [29] M. Mehring, J. Mende and W. Scherer, *quant-ph/0209137*.
- [30] A. V. Balatsky, Y. Manassen and R. Salem, *Phys. Rev.* **B66**, 195416 (2002).
- [31] A. Barenco, C. H. Bennett, R. Cleve, D. P. DiVincenzo, N. Margolus, P. Shor, T. Sleator, J. A. Smolin, and H. Weinfurter, *Phys. Rev.* **A52**, 3457 (1995).

FIG. 1. An illustration of the ENDOS scheme. A ^{13}C is placed at the STM tip. The qubits are the nuclear spins of ^{31}P ion deposited on the surface of ^{28}Si substrate. When the STM tip approaches an ion, it changes the contact interaction and resonance frequency.

